# SmartHome
RGBCW Led Light Controller

SHL LC1

SmartHome RGBCW Led Light Controller

Key Properties

- Controlling LED Strips of all types

- Zigbee Version

- Easy Installation

- Controlling via Antik SmartHome APP

- Compact Design

45mm

18mm

115mm

Reset Button

Description

The LED strip Zigbee controller is designed to control your LED strips of all types, i.e. single color, dual color, RGB, RGB+WW (or RGB+CW) & RGB+WW+CW via Antik SmartHome APP.

Installation

1. Installation must be carried out by a qualified electrician in accordance with local regulations.
2. Keep the device out of reach of children.
3. Keep the device away from water, damp or hot environment.
4. Install the device away from strong signal sources such as microwave oven that may cause signal interruption resulted to abnormal operation of the device.
5. Obstruction by concrete wall or metallic materials may reduce the effective operation range of the device and should be avoided.
6. Do not attempt to disassemble, repair or modify the device.

Technical Specifications

Voltage	CD 12V / 24V
Max. Load	96W (12V) / 192W (24V) for LED
Wireless Frequency	2.4GHz ~ 2.484GHz IEEE 802.15.4
Operation Temperature	-20˚C ~ 50˚C
Case Temperature (Max)	80˚C
Operation Range	200 m
Dimensions (WxDxH)	115 x 45 x 18 mm
Ingress Protection	IP 20
Warranty	2 Years

SmartHome

LED Light Controller

SHL LC1

+421 55 30 12345   info@antiksmarthome.com   www.antiksmarthome.com